LEVELL

R.C. OSCILLATORS

TYPE TG200 SERIES

INSTRUCTION MANUAL

OPERATING INSTRUCTIONS

for

R.C. OSCILLATORS
TYPE TG200 SERIES

GUARANTEE

We undertake to repair, or replace free of charge, any components that fail within 12 months of the date of purchase of an instrument provided that the instrument is not, in our opinion, modified or misused. Instruments returned by post should be well packed to avoid damage. We recommend the use of two strong cartons, one to fit closely around the instrument and the other large enough to float the small carton in at least 2" thickness of wood wool.

LEVELL ELECTRONICS LIMITED, MOXON STREET, BARNET, HERTS.,ENGLAND.

Telephone: 01-440 8686
01-449 5028

We hope you are satisfied with this instrument. May we send you details of the following items that we supply?

INSTRUMENTS

AC AMPLIFIERS
AC MICROVOLTMETERS AND dB METERS
BROADBAND VOLTMETERS
DC MICROVOLTMETERS / NULL DETECTORS
DC MULTIMETERS
DECADE CAPACITANCE BOXES
DECADE RESISTANCE BOXES
FREQUENCY COUNTERS
FUNCTION GENERATORS
INSULATION TESTERS
MULTITESTERS
OSCILLOSCOPES
RC OSCILLATORS - ANALOGUE TUNED
RC OSCILLATORS - DIGITAL TUNED
TRANSISTOR TESTERS

ACCESSORIES

CARRYING CASES
MAINS POWER SUPPLY UNITS
PROBES AND TEST LEADS

LEVELL ELECTRONICS LIMITED
MOXON STREET, BARNET, HERTS., EN5 5SD. ENGLAND.
TELEPHONE: 01-440 8686 AND 01-449 5028.



- **1Hz to 1MHz**
- **SINE OR SQUARE**
- **7Vr.m.s. OUTPUT**
- **LOW DISTORTION**
- **SYNC. FACILITY**
- **STABLE AMPLITUDE**

A frequency coverage of 1Hz to 1MHz is provided on these solid state R.C. Oscillators which are available in versions that generate sine waves only or sine and square waves with a fine frequency control on one version to permit incremental changes as small as 0.03%. An output up to 7V r.m.s. is generated by all versions but choice is available as to whether or not an output meter is fitted. Internal long life batteries provide power for these instruments but operation from an A.C. mains supply is possible when a LEVELL stabilised Power Supply Unit is fitted in place of the batteries.

The patented oscillator circuit arrangement uses a single track linear potentiometer as the variable frequency control. This gives a much longer working life for the component when compared with the dual track logarithmic potentiometers that are often used in Wien bridge circuits. In addition, variation of the potentiometer over the audio range is not accompanied by amplitude bounce which is characteristic of Wien bridge circuits. The output of the oscillator is stabilised by a thermistor and considerable negative feedback is applied to ensure that the waveform has a low harmonic content.

The square wave output of the dual waveform versions is produced by a trigger circuit to ensure that the rise time is irrespective of the frequency.

The output from the oscillator circuit, or the trigger circuit, is fed to the output terminals via a low distortion power amplifier. This acts as a buffer to prevent modulation of the oscillator by signals picked up on the output leads. A sync. socket is provided to give a constant sinusoidal signal for locking other equipment such as an oscilloscope time base. The oscillator can also be locked to an external signal which is fed into the sync. socket.

VARIATIONS

Type TG200 : Sine wave output only. No output meter.
Type TG200D : Sine and square wave outputs. No output meter.
Type TG200M : Sine wave output only. Output meter fitted.
Type TG200DM : Sine and square wave outputs. Output meter fitted.
Type TG200DMP : As type TG200DM plus 0 to 1% calibrated fine frequency control.

FREQUENCY COVERAGE

1Hz to 1MHz in 12 overlapping ranges.

FREQUENCY ACCURACY

$\pm$1.5% $\pm$ 0.01Hz up to 100kHz, $\pm$2% up to 1MHz.

FREQUENCY STABILITY

Change of frequency for $\pm$15% shift on 33V supply is $<\pm$0.1% from 1Hz to 50kHz.
Change of frequency with temperature is $<\pm$ 0.025%/^{o}C.

OUTPUT AMPLITUDE

7V r.m.s. (20V p-p on sine) source voltage reducible to <200μV by a continuously variable control and switched attenuator with 10dB steps up to 70dB. Power output -74dBm/+13dBm (20mW) into 600Ω.

OUTPUT ACCURACY

Versions with a meter are calibrated 0 to 7V r.m.s. source voltage, accuracy $\pm$2% f.s.d.
Versions without a meter have the output control calibrated 0 to 7V r.m.s., accuracy $\pm$5% $\pm$5% f.s.d.
Additional scales cover 0 to 2V and -14dBm to +3dBm. The attenuator error on 2V, 700mV, 200mV and 70mV is $\pm$2% and on 20mV, 7mV and 2mV is $\pm$4%.

OUTPUT IMPEDANCE

600Ω $\pm$1% at all settings of the amplitude controls.

SINE WAVE DISTORTION

Harmonic content is <0.05% from 50Hz to 15kHz, <0.1% from 10Hz to 50kHz, <0.2% from 5Hz to 150kHz and <1% at 1Hz and 1MHz. These limits apply at a supply voltage of 33V -5% to +15%, they double at 33V -15%.

SINE WAVE AMPLITUDE STABILITY

Amplitude variation with frequency is $<\pm$1% up to 300kHz and $<\pm$3% at 1MHz.
Amplitude variation with temperature is $<\pm$0.3%/^{o}C. Amplitude variation for $\pm$15% change on 33V supply is $<\pm$0.1% up to 150kHz and $<\pm$0.3% at 1MHz.

SQUARE WAVE CHARACTERISTICS

Rise time is <150nS with no droop at low frequencies. Variation of p-p amplitude with frequency is $<\pm$1% up to 300kHz and $<\pm$3% at 1MHz. The r.m.s. amplitude falls about 10% at 1MHz due to rise time. Amplitude variation is $<\pm$0.2%/^{o}C and $<\pm$3% for $\pm$15% change on 33V supply.

SYNC OUTPUT

Sine wave in phase with the output, amplitude is >1V r.m.s., source resistance 3.3kΩ.

SYNC INPUT

The frequency can be locked to an external signal over a range of $\pm$1% per volt r.m.s. input up to 10V maximum. The frequency control then varies the phase of the output.

TEMPERATURE

The above characteristics are at 18^{o}C to 28^{o}C with only minor divergencies from -5^{o}C to +45^{o}C.

POWER SUPPLY

Four Ever Ready type PP9 batteries provide 33V $\pm$15% centre earthed supply. Consumption is typically 12mA on sine and 16mA on square waves giving an average battery life of 300 hours. Operation from A.C. mains is possible when LEVELL Power Unit type PU33 is fitted in place of the batteries. The Power Unit output is 33V $\pm$5% stabilised against supply variations.

SIZE & WEIGHT

180mm x 260mm x 140mm. 4.5kg.

CARRYING CASES

Cases are available as optional extras. They are stiffened with board and felt lined. Shoulder straps are detachable and it is possible to use an instrument whilst in a case.

OPERATING INSTRUCTIONS FOR LEVELL TG200 R.C. OSCILLATORS

1. Connection of Power Supply

Remove the back panel from the case and connect four 9V batteries Ever Ready type PP9 or equivalent by means of the snap fastener connections provided.

A LEVELL Power Supply Unit type PU33 may be fitted in place of the batteries when operation is required from an A.C. mains supply. The earth connection on the Power Unit must be joined to the case of the instrument.

Replace the back panel taking care to ensure that the back screws are tight so that there is a good electrical connection between the back panel and the instrument case.

2. To Check Supply

Types TG200M, TG200DM and TG200DMP are fitted with a meter that should have the mechanical set zero screw adjusted when the instrument is switched to the OFF position. The attenuator switch should be set to the "Test supply" position and 10 seconds allowed for the pointer to settle to a stable reading. The supply limits are marked on the meter scale.

Types TG200 and TG200D are fitted with an indicator lamp that glows in the "Test Supply" condition when the instrument is fitted with batteries that are in good condition.

3. To Use the Oscillator

Turn the two "Amplitude" controls fully clockwise to obtain maximum output from the oscillator. Allow 30 seconds for the oscillator to settle to a steady state after switching on. The frequency may then be varied by adjustment of the range switch and frequency dial.

The output waveform of type TG200D, TG200DM and TG200DMP may be selected to be sine or square by means of the slide switch that is pictorially marked. However, the output on the "SYNC" socket remains a constant amplitude sine wave irrespective of the settings of the amplitude controls and the Sine/square switch.

The amplitude control switch is marked in terms of both voltage and dBm. The voltage markings refer to the r.m.s. source voltage that is indicated at the upper ends of the voltage scales on the meters of types TG200M, TG200DM and TG200DMP or the calibrated amplitude potentiometers of types TG200 and TG200D. The amplitude control switch introduces attenuation in steps of 10dB up to 70dB in series with the output terminals of the oscillator. The control is marked in terms of dBm with 0dBm meaning a power level of 1mW produced into a load of 600Ω. The control steps of 10dBm from -60dBm to +10dBm are added to the reading on the calibrated scale of -14dBm to +3dBm in order to give the available power level into a termination of 600Ω.

Fine adjustment of the output level is made by the amplitude control potentiometer that varies the signal level over a range of at least 20dB without affecting the output impedance of the oscillator which remains at 600Ω at all output levels and all frequencies. It is not necessary to terminate the oscillator with a matched load of 600Ω as variation of the load impedance has a negligible effect upon the oscillator frequency. Low load impedances may be placed across the output terminals to obtain output currents up to 11mA r.m.s. This feature permits a resistor of say 82Ω to be placed across the output terminals to lower the source impedance to 72Ω for driving a coaxial cable of this characteristic impedance. Matching of the source to the load becomes mainly of importance at the high frequency end of the oscillator range on square wave output when it is desired to maintain a fast rise time and avoid creating H.F. ringing in reactive loads and test leads.

The frequency range switch is marked alternately with a dot and a star which refer to the two scales that exist on the variable frequency control. The numbers on either side of the symbol give the limits in Hz at each end of the selected range.

4. To Use The SYNC. Facility

There are two uses for the socket marked SYNC. The first is to provide a sine wave signal output of constant amplitude of about 1.5V r.m.s. for synchronising other items such as an oscilloscope time base. The second use is to accept a signal input to lock the oscillator to another source.

The sync. output can be used to drive a load impedance of the order of 100kΩ in parallel with 50pF with negligible effect upon the oscillator performance. Placing a short circuit between the sync. socket and earth only affects the oscillator by pulling the frequency about 1% at the very top end of the frequency coverage.

The lock facility permits the oscillator to be synchronised to a low level frequency standard such as a crystal controlled oscillator that can provide an output of about 1V r.m.s. into a load of 3.3kΩ. The main oscillator output then becomes a standard source when the frequency dial is tuned to the frequency of the crystal controlled oscillator. In this respect the oscillator may be considered as then acting as a tuned power amplifier with the advantage that the output level is stabilised against amplitude variations on the output of the crystal controlled oscillator.

5. Adjustment of Preset Controls

A number of preset adjustments are provided to permit optimum setting of the performance of the instrument. These adjustments are set prior to despatch of the instrument from the factory when operating from supplies of ±16.5V ±5% at a temperature of 20°C to 25°C. Readjustment of these controls will not normally be required for many months unless the instrument has had a component failure.

The following items of test equipment are required during the process of adjustment of the preset controls:-

(a) Frequency meter capable of measuring frequencies from 100Hz to 1MHz to an accuracy better than ±0.1%.

(b) D.C. Voltmeter with sensitivity better than ±10mV and input impedance greater than 10kΩ.

(c) A.C. Voltmeter with calibration accuracy better than ±0.5% at 5V 1kHz and input impedance greater than 500kΩ.

The first 10 adjustments are made to controls located on the main printed circuit board which is visible when the back panel is removed. The two square wave adjustments are located on the small printed circuit board that is behind the battery compartment at the centre of the instrument. The positions of the various controls can be seen on the following diagram.

Adjustments must be made in the following order:-

(1) Set to 5V output on sine waves at 1kHz. Place the D.C. Voltmeter across the output connections. Adjust the Z control for <± 10mV D.C. on the output.

(2) Transfer the D.C. Voltmeter to measure between the SYNC. socket and earth. There should be a potential of about -70mV present on the 1kHz to 3kHz range. Switch to the 3Hz to 10Hz range and adjust the S control at 10Hz until the same D.C. level is obtained.

(3) On TG200M, TG200DM and TG200DMP, adjust the METER control to vary the sensitivity of the meter so that it reads correct at 5V output from the oscillator at 1kHz on sine wave.

(4) On TG200M, TG200DM and TG200DMP, turn the amplitude control to maximum and adjust the SINE control so the output is 7.5V measured on a meter across the output terminals. On the TG200 and TG200D, turn the amplitude control to 5V on the calibrated scale and adjust the SINE control so the output is 5V across the output terminals.

(5) Set the amplitude to 5V approximately and adjust the frequency controls until the frequency on the 100Hz to 300Hz range is set at 100Hz i.e. the period is 10,000µS. Turn only the range switch to the 3kHz to 10kHz range and adjust TC1 + TC2 until the frequency is 3162.3Hz i.e. the period is 316.23µS. Increasing either TC1 or TC2 reduces the frequency.

(6) Set the frequency on the 100Hz to 300Hz range to 300Hz i.e. a period of 3333.3µS. Turn only the range switch to the 3kHz to 10kHz range and measure the frequency. It should be 9486.9Hz ± 0.1% i.e. the period should be 105.41µS ± 0.1%.

When the measured value is outside these limits adjust the upper trimmer TC2 to give an error in the opposite direction of twice the magnitude of the observed error and then adjust the lower trimmer TC1 to correct this error i.e. if the period measured was 105.0µS instead of 105.41µS, adjust TC2 until the period is 106.23µS and then adjust TC2 to obtain 105.41µS.

The object of this method of adjustment is to vary the capacity ratio TC1:TC2 but not to vary the product capacity of TC1 X TC2 as this affects the preceding adjustment at the low end of the scale. Repeat (5) and (6) until no further adjustment is required.

(7) Turn to the 3kHz to 10kHz range and adjust the L control at 4kHz setting on the frequency dial.

(8) Rotate the dial to 8kHz and adjust the H control to obtain the correct frequency. Observe the errors present at dial settings of 3, 4, 5, 6..... 10kHz. The errors at all points should be less than $\pm$ 1%. Adjust the L and H controls in order to obtain optimum tracking i.e. to balance the errors so that no cardinal point is worse than $\pm$ 1% in error.

(9) Adjust the 300kHz trimmer so that the error at 300kHz is balanced to minimum at the 300kHz points on the top 2 ranges. Place the back panel in position before taking measurements as the frequency is affected by the presence of this screening plate.

(10) Adjust the 1MHz trimmer so that tracking is optimum from 700kHz to 1MHz with the back panel in position. Repeat (9) and (10) until optimum conditions are obtained for the tracking of the scale on the top two ranges.

(11) On TG200D, TG200DM and TG200DMP adjust the square wave D.C. zero control until the D.C. level superimposed on a 5V 1kHz output is less than $\pm$10mV.

(12) On TG200D, TG200DM and TG200DMP adjust the square wave output control until the r.m.s. output on square waves is same as that on sine waves at 5V 1kHz.

PRESET ADJUSTMENTS OF TG200 SERIES



SETTING ORDER & CONDITIONS

(3) 5V output at 1kHz on sine wave. Absent on TG200 and TG200D.

(1) D.C. zero on sine output at 5V 1kHz.

(4) 7.5V maximum output at 1kHz on TG200M and TG200DM. 5V at 5V on scale of TG200 and TG200D.

(7) At low end of frequency scale in conjunction with H control.

(9) For 300kHz optimum on top two ranges (Interacts with 1M control)

(8) At high end of frequency scale in conjunction with L control for optimum tracking on 3kHz to 10kHz.

(2) For same D.C. level on SYNC at 10Hz as exists at 2kHz.

(5) TC1 + TC2 set so frequency is 3162.3Hz on 3-10kHz at same dial setting as that giving 100Hz on 100-300Hz.

(10) For 700kHz to 1MHz optimum tracking. (Interacts with 300kHz control)

(6) TC1 : TC2 set so frequency is 9486.9Hz on 3-10kHz at same dial setting as that giving 300Hz on 100-300Hz.



(12) R.M.S. output on square to be same as sine at 5V 1kHz.

(11) D.C. zero on sq. output at 5V 1kHz.

CONNECTIONS FOR PP9 BATTERIES IN TG200 SERIES



CONNECTIONS FOR PU33 IN TG200 SERIES




TG200DMP ONLY
2.2K
43K 2%
8.2p
+18V
7.5K
C4V7
1000µ 18V
0·1µ
10M
S
5K
10K
820Ω
15K
10K 2%
L
5K
4.7K
22p
2.2K
+0·7V
6.98K 1%
6.98K 1%
10Ω
-80mV
470µ 6.3V
2.2K
0·33µ
TC1
560p
10-80
100Ω SET 1MHz
2.2p
470K
1K
10p
200p
.01µ
1000µ 18V
0.2µ 2.5%
TC2
560p
10-80
3.3Ω
820K
3.3K
8.2p
220µ 4V
12K
1p
2.2p
3.3K
22K
.01µ
8.2p
-8.2V
-18V
H
1K
10K
FREQUENCY
1.02K 1%
22p
3.3K
TC4
0.5-3.5
+1·4V
2.2K
15K
820Ω
1.2K
470Ω
100Ω
470p
15K
RA54
22K
9
SINE
2.7K
1K
1.5K
1.5p
3.9K
3.9K
SYNC
2.2K
AMPLITUDE
10Ω
6.8K
22p
Z
10K
C8V2
3.9K
200p
8.2K
6.8p
1000p
18Ω
18Ω
1p
1.1K
.01µ
CZ10
12K
TRANSISTORS
NPN- ME4102
PNP - ME0412
DIODES
D1 & 2 IN4001
OTHERS IN4148
S2 1F
S2 2F
60.4K 1%
604Ω 1%
87.8Ω 1%
190Ω 1%
600Ω 1%
515Ω 1%
350Ω 1%
1.30K 1%
56K
604Ω 1%
S1 1F
S1 2R
1.8Ω
METER
3.0K
1.15K 1%
1K
56K
1.40K 1%
1.5K
TG200M, DM & DMP
220µ 10V
TG200D, DM & DMP
S3A
S3B
S3C
1K
3.3K
10K
5.6K 2%
7.5K 1%
4.7p
180K
43K 2%
4.3K 2%
43K 2%
10K
1.02K 1%
2.21K 1%
6.98K 1%
22.1K 1%
69.8K 1%
221K 1%
698K 1%
S2 1R
S2 2R
TG200M, DM & DMP
1.40K 1%
33Ω
OUTPUT
1000p
S1 1R
S1 2F
TG200 & 200D
180Ω 19V 97mA
+18V
-18V
Issue: 10
LEVELL
R.C. OSCILLATORS TYPE TG200 SERIES
RESISTORS ARE ± 5% UNLESS MARKED



PRINTED SIDE OF TG200DMP PRINTED CIRCUIT.



COMPONENT SIDE OF TG200DMP PRINTED CIRCUIT.

www.manualsplus.com
1004251